

Practice Real CCNA Voice CME Labs with GNS3 and Softphones

In Order to test the CME setup, here is a small lab that i did. Since I don't have a voice router yet i had to the whole lab in GNS3. Here is what i used: (1) Cisco 3750 router with 128D/16F (2) Ipblue (to emulate a 7940 phone) (3) CIPC (to emulate a 7970 phone) (4) SolarWinds TFTP I ran this lab in a Windows XO Virtual Machine with 3gb Ram and a dual-core AMD proc. the steps were very easy and i followed what we discussed in the the study notes. **Steps:** (1) Configured the FE interface with 172.16.1.1/24 (2) Copied the phone configuration files from the tftp server (at 172.16.1.150) using the command: `arc tar /xtract tftp://172.16.1.150/phonefile.tar flash:` * Note: You can download the whole CME package. I had to do this for just this lab. (3) Make the downloaded files available using the `tftp-server flash:filename` (4) Enable the dhcp server settings, with the Option 150 command. (5) Specify the Dn's and the Ephone's under the telephony-service options. (6) Load the specific phone loads using the `load` command (7) Don't forget to do the "create cnf-file" command. (At this point your connected phones should be able to get an ip, download all the necessary files and register with the cme router) (8) Next configure some Dn's, with phone numbers. (9) Bind the phones with the dn's and assign them with the "button" command. (10) Restart either by issuing the `restart` command under the ephones or under the telephony-service. And that should do it, your phones at this point will be able to call each other.



SolarWinds TFTP Server Log:

```
TFTP connected from 172.16.1.1:52679 on 10/17/2009 12:24:56 AM, binary, GET. Completed, file name:
TFTP connected from 172.16.1.1:52679 on 10/17/2009 12:24:24 AM, binary, GET. Started, file name: C
TFTP connected from 172.16.1.1:54835 on 10/17/2009 12:24:24 AM, binary, GET. Interrupted by client
TFTP connected from 172.16.1.1:54835 on 10/17/2009 12:24:24 AM, binary, GET. Started, file name: C
TFTP Server Service Started [UDP - 69].
```

Telnet Terminal Output:

```
CME-Router#
CME-Router#
CME-Router#arc
CME-Router#archive tar /xtract tftp://172.16.1.150/7940.tar flash:
Loading 7940.tar from 172.16.1.150 (via FastEthernet0/0): ?
extracting P00308000500.bin (129824 bytes)!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
extracting P00308000500.loads (458 bytes)
extracting P00308000500.sb2 (705536 bytes)!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
extracting P00308000500.sbn (130228 bytes)!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!!
[OK - 969728 bytes]
CME-Router#sh flash:
System CompactFlash directory:
File Length Name/status
1 129824 P00308000500.bin
2 458 P00308000500.loads
3 705536 P00308000500.sb2
4 130228 P00308000500.sbn
[966304 bytes used, 15810908 available, 16777212 total]
16384K bytes of ATA System CompactFlash (Read/Write)
CME-Router#archive tar /xtract tftp://172.16.1.150/c_tar flash:
```

Call Log:

Time	From	To	Status
4 47a 10/17/09	1213	1212	Connected

Call in Progress:

10/17/2009 12:47:57 AM 1213
 Connected to 1212 07
 Connected

Buttons: Hold, EndCall, Transfer, More>>

Keypad: 1-9, *, 0, #, Hold, EndCall, Transfer, More>>

Here is the download link: [SD \(edited\) Flash/Mp4 File ~ 25mb](#); Click Me Remember this is just to see how the whole system works, there are a zillion different options that you can configure. We will and I promise you, will discuss and try to implement as much as we can. I hope this lab was informative, and stay tuned for more.