

CCNA ICND2 Lab 1 - Change Router Name and Password

Lab Topology:



Lab Requirements: 1. Router name: router 2. Set **password** to **cisco**, **secret** to **cisco**, and **vty** to **cisco**. 3 All the passwords are required to be encrypted. **Lab Process:** Router>enable Router#configure terminal

```
Router(config)#hostname router ; / router set route name Router(config)#enable
password cisco ; / cisco set router password Router(config)#enable secret
cisco ; / set router encryption password Router(config)#line vty 0
Router(config-line)#login Router(config-line)#password cisco ; / require password
authentication Router(config-line)#exit Router(config)#service password-encryption ; / set global
password encryption
```